

## LG-Aria-LDK-30 EXE

### To make a call

- Pick up handset and/or Dial [ 9 ] ( 0 for Reception)

### To answer a call

Pick up handset or press [ MON ] Button.

### To transfer a call

Press [ TRANS/PGM ] Button,  
Dial Extension No (200 + ) (or Flexible button)  
(option Announce call )  
Hang up.

### To Park Calls

Press [ TRANS/PGM ] Button  
Dial 601 – 619  
Hang up.

### To Retrieve

Pick up Handset or press [ MON ] Button.  
Dial 601 – 619

### To Intercom

Pick up Handset or press [ MON ] Button.  
Dial Extension No ( 200 + )

### To Page

Pick up Handset  
Dial #00 (or Flexible button)

### Meet me Page

Pick up Handset  
Dial ## to be connected to the paging party

PH: 1300 799711

**Callback**

- **Set**

Dialled Busy Extension  
Press [ TRANS/PGM ] Button  
Dial 56

- **Answer**

To Answer Callback message  
Dial 57 or Ext. No. on display

**Call Forward**

- **Set**

Dial 54,  
1 – Direct  
2 – On Busy  
3 – No Answer  
4 – Busy / No Answer,  
Dial Ext No (200 +),  
press [ MON ] Button

- **Cancel**

Dial 54  
#

**Call Wait/Camp-On**

Press Trans,  
Dial Ext No (200 +),  
Press \* and Hang up to complete transfer

**Redial**

Dial 52

**Program Flexible Button**

Press [ TRANS/PGM ], Press [ Flexible button ]  
Dial Feature eg. Extension No.(2xx),  
Press [ Hold/Save ], Press [ Mon ]

**Group Pick Up**

(will answer the longest  
ringing call)

Pick up Handset  
Press \* \*

**Differential Ring**

Press [ TRANS/PGM ]  
Dial 50  
Dial 1, 2, 3 or 4  
Press [ HOLD/SAVE ] to select



PH: 1300 799711

